

# SSY0079 - *Single Axis CMOS Signal Conditioning Module*

## > *Open Architecture*

The **SSY0079 Single Axis CMOS Signal Conditioning Module** is a DC input/output operated device, which operates off a single ended supply, and provides a bipolar DC output. Specifically designed to interface directly with all Spectron *Single Axis Tilt Sensors*, and with the *SP5000 Series Dual Axis Tilt Sensor* (operating in single axis mode), this low power consumption conditioner is ideal for battery driven applications, while the open architecture design affords easy installation and adjustment access for OEM's. The module internally converts the DC input voltage into an AC excitation voltage for the sensor, and demodulates the sensor output into a smooth amplified DC output voltage. Incorporating a proprietary signal processing algorithm, and an external temperature compensation sensor (optional), normal measurement errors are severely reduced. The **SSY0079** also features overload protection, and is 100% reliability tested to provide the highest quality available.



### General Specifications

Input voltage .....	+5Vdc to +15Vdc
Input current .....	0.5mA @ +5Vdc, 0.9mA @ +15Vdc
Sensor excitation .....	3V pp, square wave
Input impedance .....	5 megohms
Output .....	+/-1.5Vdc @+6Vdc supply, referenced to Vref
	<i>Note; minimum output = 50mVdc + (supply voltage . 1.5Vdc)</i>
Load .....	100k ohm minimum
Time constant .....	70 msec
Offset adjustment .....	+/-45 mVdc
Output ripple .....	0.35% of output voltage (RG 24k ohm)
Temperature coefficients (module w/out sensor)	
- Null .....	100 microvolts / Co (typical)
- Scale .....	0.02% / C° @ +1Vdc output
Output short duration .....	Continuous (Vout and Vref)
Temperature range	
- Operating .....	-25 to +70C°
- Storage .....	-40 to +80C°
Temperature Compensation	
-	Temperature compensation of the assembly (module and sensor) can be accomplished using an external silicon temperature sensor (KTY81-120) and a resistor (SBT). Exact resistor value is determined by placing a decade resistor box across R3, and adjusting until desired results is obtained. With this configuration, it is possible to reduce the scale temperature coefficient error from a 0.3%/C° (nominal), to 0.03%/C° (nominal). Please see wiring diagram for connection points.



**SPECTRON SYSTEMS TECHNOLOGY INC.**

595 OLD WILLETS PATH  
HAUPPAUGE NY 11788  
PHONE: 631 582-5600  
FAX: 631 582-5671



**Specifications subject to change without notice!**


Doc.# SDS-123-1805

# SSY0079 - Single Axis CMOS Signal Conditioning Module

## > Open Architecture

### Dimensions, Electrical Connections, and Adjustments

mm (inches)



**SPECTRON SYSTEMS TECHNOLOGY INC.**

595 OLD WILLETS PATH  
 HAUPPAUGE NY 11788  
 PHONE: 631 582-5600  
 FAX: 631 582-5671



*Specifications subject to change without notice!*

Doc.# SDS-123-1805